

Hsin Lin Computer 1100CX "Enhance 2S1P"
8-bit 2 serial 1 printer card
FCC ID: I8PHLC-1100CX
Uses 16C552 chip

RS232-1

I/O	JP2-1	JP2-2	IRQ	JP1
3F8	0	0	2/9	I-J
2E8	0	C	3	I-H
3E8	C	0	4	B-A
Disable	C	C	5	B-C

RS232-2

I/O	JP2-3	JP2-4	IRQ	JP1
2F8	0	0	2/9	K-J
3E8	0	C	3	D-E
2E8	C	0	4	K-L
Disable	C	C	5	D-C

LPT

I/O	JP2-5	JP2-6	IRQ	JP1
3BC	0	0	3	F-E
278	0	C	4	M-L
378	C	0	5	M-N
Disable	C	C	7	F-G

LPT Mode	JP2-7
Normal	C
Enhanced	0